

NightMatic:3000 Vario

Automatically switches light 'ON' and 'OFF':

Saving no end of energy.

Did I turn the light 'OFF'? Or did I forget to? With the NightMatic 3000 Vario, this question's not an issue any more. When it's dark it takes care of switching the outside light 'ON' and 'OFF' all by itself. But that's not all. The intelligent night-economy mode automatically switches the light 'OFF' after a programmable time and back 'ON' again in the early hours between 4 and 6 o'clock. The photo-cell controller feels most at home on your property, on the front of a building or in a shop window.



Twilight switch
+ eco-mode



IP54

1000W
max.



0,5 - 10 lux



energy
saving

3 JAHRE
GARANTIE

functional
warranty



EAN NightMatic:3000 Vario white	4007841 550615
EAN NightMatic:3000 Vario black	4007841 550516
Type	photo-cell controller
Dimensions (h x w x d)	89 x 74 x 37 mm
Power supply	230 - 240V/50Hz
Where to use	outdoors
Installation	wall
Max. output (uncorrected, inductive, cos φ = 0,5, e.g. fluorescent lamps)	1,000 W
Response brightness	approx. 0,5 - 10 lux / at press of button
Night economy mode	variable night 'OFF' time
Intrinsic power consumption	< 0,8 W
IP rating	IP54
Protection class	II


For wall mounting



white



black



UV-resistant plastic

